

- 1 -

MAGNETIC DISK DEVICE AND SERVO WRITE METHOD

BACKGROUND OF THE INVENTION

The present invention generally relates to magnetic disk devices such as hard disk drives, and particularly to a technique of writing servo signals
5 for positioning magnetic heads on magnetic disks.

As one of servo write methods, there is known the self servo-write method for recording servo track information in a magnetic disk device by controlling the magnetic head (hereafter, simply referred to as
10 head) and actuator of a product itself without using any external writing device. This method is concretely disclosed in Japanese Patent No. 2921604 (W096/28814) and JP-A-8-255448.

In the former, reference information for
15 positioning a head, i.e., a servo signal, is written after a head is pressed against a stopper, and the amount of head-feeding, or pitch for positioning is calculated while being adjusted according to the amplitude of its reproduced waveform.

20 In the latter, the magnetic head is moved by using an external writing device within a clean room so that servo information as a reference can be previously recorded on a part of a magnetic disk (hereafter, simply referred to as disk), and the amount of head-
25 feeding, or pitch for positioning is calculated by

reading the recorded pattern.

In the former, however, the regions over which information is written on the disk cannot be fixed, or determined because the head's core width varies, i.e., because very small read and write elements have their tolerances of mounting or size.

Moreover, in order to execute the latter, it is necessary to record a servo signal on part of the disk by using an external writing device. Thus, the latter has the drawback that it spoils the advantage of the self servo-write that does not need any external writing device. In addition, it requires a clean room as a large-scale facility.

SUMMARY OF THE INVENTION

The present invention is to provide the self servo-write capable of removing the necessity of using an external writing device for recording a preliminary servo signal, and definitely determining an information writing region by use of the magnetic disk device itself on the disk that this device has, thereby assuring a designed number of tracks to be recorded in this fixed region.

The above objective of the invention can be achieved by providing a magnetic disk device in which a servo-write method is executed by writing a recording region detecting signal on a magnetic disk that the magnetic disk device has when a magnetic head the

device itself has is initially loaded onto the disk at a stage where a positioning signal for the head is not recorded yet, and determining a servo signal writing region of the magnetic disk on the basis of the
5 position where the recording region detecting signal has been written on the disk.

According to the invention, the amount the head is fed when the servo signal is written can be adjusted on the basis of the amount the head is fed
10 according to a propagation-purpose pattern recorded in the radius direction of the disk between the ends of the servo signal writing region with one end selected as the position at which the recording region detecting signal has been written and with the other end selected
15 as a stop position at which the head is stopped by, for example, a stopper.

In addition, the magnetic disk device of the invention has a magnetic disk for storing information, a magnetic record head for recording information on the
20 disk, and a magnetic reproduce head for reproducing information from the disk, wherein the recording region detecting signal is written on the disk just when the head is loaded onto the disk on which any positioning signal for the head is not stored yet, and a region of
25 tracks to be recorded on the disk is determined on the basis of the position at which the recording region detecting signal has been written.

Moreover, according to the invention, just

when the head is initially moved, or fed onto the disk from, for example, a ramp road on the outer periphery side, a current is caused to flow to the head, thereby writing a signal on the disk along the outermost

5 periphery. Then, the head is further fed toward the inner periphery side, and fed back toward the outer periphery side. When it is fed back toward the outer periphery, the propagation-purpose signal is written at a certain pitch. At this time, the signal written when
10 the head is initially loaded onto the disk will be detected. This detected signal is recognized as the outermost periphery of the region over which information is to be written on the disk. Thus, a track pitch necessary when a product-purpose servo
15 signal is written can be calculated from the distance between the innermost periphery and the outermost periphery, and from a designed number of tracks. Therefore, since the servo-write can be performed by use of the head that the magnetic disk device itself
20 has, it is not necessary to record servo tracks within a clean room by using an external writing device as in the prior art.

Additionally, according to the invention, since the track region is provided between the position
25 at which the recording region detecting signal is written, and the stop position at which the head is stopped by a stopper, servo tracks can be recorded by the magnetic head that each magnetic disk device has.

In addition, the recording region detecting signal is written in the loading area between the ramp road and the servo signal. Also, since the write current is caused to flow to the head only during the
5 time interval from when the magnetic head lies at a constant position on the ramp road to just when the magnetic head is loaded onto the disk, the recording region detecting signal can be written at a predetermined position on the magnetic disk.

10 Additionally, the time duration, or transition time in which the magnetic head is initially loaded onto the disk from a constant position at which the disk lies on the ramp road can be calculated from the distance the magnetic head has been moved and the speed at which the
15 head is moved, by means for making such calculation. According to the invention, the servo region can be easily determined by using the head the magnetic disk device itself has.

Moreover, when the head is fed back from the
20 stop position to which the head is regulated in its movement by the stopper to sequentially record the propagation-purpose pattern in the radius direction of the disk, and detects the recording region detected signal, the detected position is recognized as one end
25 of the track region, thus making it possible to easily find the servo signal recorded region.

Additionally, the pitch at which the head is fed to record a product-purpose servo signal can be

calculated from the number of times that the head is fed, to record the propagation-purpose pattern, back from the stop position to which the head is regulated by the stopper until the recording region detecting
5 signal is detected, and from a designed number of tracks, thus making it possible to assure the designed number of tracks.

According to the invention, when the magnetic disk device makes self servo-write operation, the
10 information written region on the magnetic disk can be determined by the head the device itself has, so that the designed number of tracks can be assured. Therefore, it is not necessary to provide an external writing device and a writing environment such as a
15 clean room.

Other objects, features and advantages of the invention will become apparent from the following description of the embodiments of the invention taken in conjunction with the accompanying drawings.

20 BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of one embodiment of the magnetic disk device according to the invention.

FIG. 2 is a flowchart for a procedure of servo write according to the invention.

25 FIGS. 3A-3C are diagrams showing the movement of a head while it is writing a pattern signal in the invention.

FIG. 4 is a flowchart for a procedure of measuring the track width of head and R/W offset.

FIG. 5 is a graph showing the relation between VCM current and head position.

5 FIG. 6 is a diagram showing the movement of head at the time of measuring track width and R/W offset.

FIG. 7 is diagram showing propagation-purpose pattern signals and reproduced waveforms of written
10 signal at the loading time.

FIG. 8 is a flowchart for a procedure of calculating the feeding pitch for servo signal for product.

FIG. 9 is a pattern diagram of propagation
15 servo signal and pattern signal.

DESCRIPTION OF THE EMBODIMENTS

An embodiment of the invention will be first described briefly. According to this embodiment, in a magnetic disk device 100 as shown in FIG. 1, a head 102
20 as a product itself is used to record a servo signal (hereafter, called servo-write) on a disk 101 in which any information is not recorded yet.

In order to make servo-write, first the disk 101 and head 102 are properly built and sealed within a
25 housing, and then a current to head 102 is instantaneously turned on and off when the head 102 is loaded, so that a signal 110 for positioning can be

recorded on the outermost periphery of the disk. The distance between the position of this recorded positioning signal 110 and the innermost periphery 111 of the disk to which the head is regulated by a stopper 106 is a recordable region's width 112 for product use. Then, servo-write is performed while the amount of head feeding is being adjusted on the basis of the track spacing calculated from the designed number of tracks.

FIG. 1 schematically shows the construction of the magnetic disk device according to the invention, and the flow of signal in the servo-write operation. This embodiment will be further described in detail with reference to FIG. 1. The magnetic disk device 100 has the disk 101 for storing information, and the head 102 for recording/reproducing a signal on/from the disk. The head 102 is supported to be rotatable around a pivot 104, and moved in any radial direction on disk 101 by an actuator 105.

In addition, a ramp road 103 is a retraction place onto which the head 102 is retreated from the disk surface. When servo-write is performed on this magnetic disk device 100, an operation control circuit unit 107 is mounted on the disk device so that it can control the head 102 and actuator 105.

As described previously, the magnetic disk device 100 of this embodiment does not use an external writing device, but use the head 102 and actuator 105 provided within itself to record signals on disk 101,

and to again record new patterns with the head offset on the basis of the reproduced signal of this recorded pattern, thus forming a servo signal on the disk recording region.

5 This operation control circuit unit 107 is not necessarily the same as one for making the magnetic disk device 100 operate as a product. The operation control circuit unit 107 includes a write current driver 107a for writing patterns, a pattern generator
10 107b, a preamplifier 107c for processing the reproduced signal, a demodulator 107d, a VCM (voice coil motor) driver 107e for driving the actuator, a controller 107f for controlling these functions, and a memory 107g for storing parameters that are required for the operation.

15 FIG. 2 shows a procedure (steps S) for servo-write operation of the magnetic disk device having those elements according to the invention. First, the spindle is started to rotate, and reached to a predetermined rotational speed (S 21).

20 Then, the actuator 105 is driven by the VCM driver 107e to move the head 102 from the ramp road 103 onto the area on the disk 101 (hereafter, referred to as loading of head) (S22).

25 At the time of loading, the write current to the head 102 is turned on so that a signal can be written on the disk 101 at the same time. A constant time after the writing of signal, the write current is turned off so that the written signal can be recorded

only on the vicinity of the outermost periphery of the disk 101 (S23).

At this time, although the head 102 lies on the disk 101, other head positioning signals are not
5 recorded yet on the disk and thus the radial position of head 102 on the disk 101 cannot be detected. Therefore, after the loading, the head 102 is not stopped but moved to the inner periphery of the disk until the actuator 105 hits the stopper 106 on the
10 innermost periphery of the disk (S24).

Thereafter, a current 109 flowing in the VCM is made constant on this innermost periphery so that the actuator can be pressed against the stopper, or that the head 102 can be substantially fixed in its
15 position. Then, the current 109 is changed to finely adjust the position of head 102, and R/W offsets and track width are measured (S25).

Further, the feed pitch is set on the basis of the information of measured track width (S26), and a
20 servo pattern (hereafter, referred to as propagation-purpose pattern) is recorded that is used to determine the head position when a servo signal is recorded later in the radial direction (S27).

When the propagation-purpose pattern is
25 recorded up to around the outermost periphery, the head 102 detects the initial pattern signal written at the time of loading, and at this time it ends the recording of propagating pattern from the innermost periphery

(S28).

Here, by using the relation between the amounts of head feeding from the inner periphery to the outer periphery, and the number of tracks of servo pattern to be written, the device calculates the pitch of head feeding for writing a servo pattern (hereafter, called product-purpose servo signal) by which the head 102 can be located at a certain track in order to write/read information (S29).

10 Then, the product-purpose servo signal is again sequentially recorded toward the inner periphery, and the servo-write operation is finished when the product-purpose servo signal of a certain number of tracks has finally been completely written (S30).

15 The feature of the magnetic disk device of the invention, as described above, is to write a signal when the head is loaded at step 22 under the condition that any positioning signal is not yet recorded on the disk, and to make the outermost periphery on which the signal 110 has been written be used as one end of the radial region 112 across which tracks are to be recorded in the radial direction.

Therefore, since the servo-write operation is performed to fix one end of the radial region across which tracks are to be recorded on the disk in the radius direction, and store the number of steps that the head has been fed over the distance from the innermost periphery to the outermost periphery in order

to record the propagation-purpose pattern, there is an advantage that, even though the head core width has a distribution, or dispersion, the number of tracks designed can be assured by recalculating the head feeding pitch that is necessary for writing the product-purpose servo signal on the basis of the ratio of the head feeding pitch to the number of tracks designed.

The procedure shown in FIG. 2 will be further described in detail. A description will be made of the procedure for the operation of writing a signal at the time of loading. First, as at step 21, when the spindle is started, the revolution speed is fixed to a predetermined value. By causing a DC current to flow to the actuator 105, the head 102 is urged to move toward the outer periphery side and pressed against the end of ramp road 103.

Then, when a DC current is again caused to flow to the actuator 105 and to move it toward the inner periphery, thereby making the loading of head 102 on the disk, a write current is simultaneously supplied to the record head at time t_1 (301) at which the head 102 lies on the ramp road 103 as shown in FIG. 3A

In this embodiment, time t_1 (301) is when the DC current is started to flow, i.e., when a counter-electromotive force from the actuator 105 is detected, and thereafter the write current to the record head is turned off when the head 110 has initially reached onto

the disk 101 (time t_2 (302)).

The write end time t_2 (302) is determined as follows. The actuator 105 is controlled by a speed control method in which the counter-electromotive force from the actuator 105 itself is detected, as shown by the velocity curve in FIG. 3B.

Therefore, the write current to the record head is turned off at time t_2 (302) corresponding to a range (303) previously decided according to the size of ramp road 103 and the outermost periphery of disk 101. Thus, the signal 110 (shown in FIG. 3C) is written along the outermost periphery of disk 101 at the same time as when the loading is made.

After the loading operation, the head 102 is fed until the actuator 105 comes in contact with the stopper 103, and the head feeding pitch is determined for the writing of propagation-purpose pattern. This procedure (steps S) will be described with reference to FIGS. 4~6.

First, after step 23 in FIG. 2, the head is moved until the actuator is made in contact with the stopper on the innermost periphery, and then a certain DC current is caused to flow in the VCM so that the actuator can be pressed against the stopper as shown in FIG. 4 (step 41).

At this time, the value of the current flowing in the VCM is represented by 109-0. Also, a pattern of a constant frequency (All-1 pattern) is

written along one full circle on the disk 101 at the radial position of the head corresponding to where the actuator has been pressed against the stopper (S42). Then, the current continuously caused to flow in the VCM in order for the actuator to be pressed is decreased in stages, and the head is started to move toward the outer periphery. FIG. 5 shows the relation between the VCM current and the radial position of the head.

10 By gradually decreasing the VCM current, which flows when the pattern has been written on the disk at step 42, as shown at 109-0, 109-1, 109-2 in turn, the head position is changed from 501-0 to 501-1, 501-2 toward the outer periphery.

15 FIG. 6 shows the relation between the radial position of the head and the amplitude of the reproduced signal. The amplitude of signal reproduced at each stage to which the head is moved is converted to a digital value by the demodulator 107d, and stored in the memory 107g through the controller 107f (S43).

20 As shown in FIG. 5, after the VCM current is decreased up to a previously selected value 109-m in order for the head to move to 501-m, it is increased up to a previously selected value 109-n in order for the head to move to position 501-n toward the inner periphery (S44).

The VCM current is again decreased from 109-n to 109-(n+1) in stages in order for the head to move to

the position where the amplitude is the maximum, and the amplitude at each stage is converted to a digital value by the demodulator 107d, and stored in the memory (S45).

5 Executing the procedure from step 401 to step 405 will form an off-track profile of reproduced amplitude as represented by reference numeral 602 in FIG. 6. The amount of R/W offset, 603 of the head is calculated from the distance between the head position
10 501-a at which the All-1 pattern has been written and the crest position (501-2, in this embodiment) of the obtained off-track profile.

 Additionally, at this stage the effective track width is calculated. Typically, the magnetic
15 track width can be represented by the distance between two points where the amplitudes in the off-track profile are 50% of the maximum.

 Thus, first, each of the values stored in the memory, and a 50% value (602-h in FIG. 6) of the
20 maximum in the off-track profile are compared with each other, i.e., the values stored in the memory that correspond to a range of the profile on the outer periphery side from the maximum amplitude point 501-2 are sequentially checked by comparing with the 50%
25 value of the maximum amplitude. The result is that a point 501-e1 where the value stored in the memory initially becomes smaller than the 50% value is decided to be the edge position on the outer periphery side.

Similarly, the values stored in the memory that correspond to the other range of the profile on the inner periphery side are sequentially checked by comparing, so that the other edge point, 501-e2, on the inner periphery side can be obtained. Thus, a track width 605 is calculated from the distance between both the obtained edges (S46).

The operation for calculating the head feeding pitch at step 25 in FIG. 2 will be next described with reference to FIG. 6. At step 26, the head is offset a certain amount from the already recorded pattern, and a new track is recorded to form a pattern in that position.

This offset movement of the head is made by positioning the head so that the amplitude of the reproduced signal from the already recorded track can reach the target value. The targeted amplitude value depends on the ratio of the head's track width to the track pitch in the associated magnetic disk device. In this embodiment, the track pitch is selected to be 125% of the measured track width 605, and half the track pitch is decided to be a head feeding pitch 604.

In this case, the targeted amplitude value for the head to be fed to record is decided to be an amplitude 602-t at a position 501-t that is separated by the R/W offset 603 and the pitch 604 away from the write position 501-a toward the outer periphery side in the off-track profile 602.

After the head 102 is fed up to the stopper 106 on the innermost periphery, the propagation-purpose pattern is recorded by the procedure of steps 24, 25 and 26. When the head 102 arrives at around the
5 outermost periphery, the signal 304 written at the time of loading is reproduced by the head 102.

FIG. 7 shows the reproduced waveforms of the propagation-purpose pattern and the signal written at the time of loading in this embodiment. A waveform
10 702a is a reproduced waveform in a place where the signal recorded at the time of loading in step 27 is not written. This reproduced waveform 702a is a waveform reproduced when a propagation-purpose pattern 701c is used as a position signal. In this case, since
15 the signal recorded at the time of loading is not written, no position signal is detected on the outer periphery side of the propagation-purpose pattern 701c.

When the head reproduces the position signal on the outermost periphery 701d in step 27, the pattern
20 signal written at the time of loading is reproduced except the propagation-purpose pattern. At this time, the reproduced waveform is a waveform 702b.

In this embodiment, the propagation pattern is detected in its amplitude at time 701a, 701b, 701c
25 (701d, 701e, 701f), and the amplitude is converted to a digital value by the demodulator 107d and supplied to the controller 107f where the signals having larger amplitudes than background noise are fed to a register

and counted.

Since the propagation-purpose pattern recorded from the inner periphery is written at a constant pitch on the disk, the number of detected signals having larger amplitudes than background noise is determined at certain points (three, as to the reproduced waveform 702a). However, on the outermost periphery, the signal written at the time of loading is also detected (four signals are detected as to the reproduced signal 702b). When more than four signals having large amplitudes than background noise are detected, the outermost periphery is detected.

When the propagation-purpose pattern is recorded up to the outermost periphery 110, the number of steps over which the head is fed can be known from the head feeding pitch 604 set in step 26. The head feeding pitch set in step 25 depends on the core width of the head, and thus the number of steps over which the head is fed varies due to the dispersion of the core width.

Thus, at the stage where the product-purpose servo signal is recorded, it becomes sometimes necessary that the feeding pitch be readjusted in order to provide a designed number of tracks. The feeding pitch of the product-purpose servo signal is readjusted according to the procedure (steps S) of FIG. 8 as follows.

The number of tracks, track pitch and head

core width designed are previously stored in the memory 107g (S81). The propagation-purpose pattern is recorded in the radius direction, and the outermost periphery is detected by recognizing the pattern
5 written at the time of loading (S82).

Until the outermost periphery is detected, the number of steps over which the head is fed in order to record the propagation-purpose pattern is counted by the controller 107f, and stored in the memory 107g
10 (S83).

Then, the number of steps for the head to be fed over is calculated by the controller 107f from the designed track number, track pitch and head core width stored in the memory 107g, and compared with the number
15 of steps over which the head has actually been fed (S84). Specifically, the number of steps can be calculated by multiplying the number of steps necessary to record one track by the number of tracks.

If the number of steps differs in both the
20 designed and actual cases, the controller 107f can find the head feeding pitch for recording the production-purpose servo signal by multiplying the pitch at which the head has actually been fed by the ratio of the number of steps over which the head has actually been
25 fed to the designed one (S85). Subsequently, the head is fed by a selected number of steps, and when the production-purpose servo signal has been completely recorded the servo-write operation is finished (S86).

A second method for detecting the outermost periphery will be described next. In this method, the surface of the disk 101 is divided into two regions that are alternately placed in the circumferential direction as shown in FIG. 9. In other words, these regions are an area 901 in which no propagation-purpose pattern is written, and an area 902 in which it is written.

At the time of loading, the signal 110 is written in the areas 901 in which no propagation-purpose pattern is written, in response to the timing signal generated from the spindle motor, and thus the areas 901 include the signal 110. The areas 901 in which no propagation-purpose pattern is written are monitored in response to the timing signal from the spindle motor. Just when the reproduced waveform of signal 110 is detected, the point of this instant is decided to be the outermost periphery.

Thus, the servo signal can be recorded at precisely a controlled track pitch by the head and actuator that the magnetic disk device itself has without recording a preliminary servo signal on a disk by using an external apparatus. Therefore, the clean room and external writing device can be omitted.

While the ramp road 103 is assumed to be on the outer periphery side in this embodiment, it may be provided on the inner periphery side provided that the positional relation between the inner and outer

peripheries is reversed in the above method, and in this case the same effect as in the above embodiment can be achieved.

It should be further understood by those
5 skilled in the art that the foregoing description has been made on embodiments of the invention and that various changes and modifications may be made in the invention without departing from the spirit of the invention and scope of the appended claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2